Qwizdom®
STUDENT REMOTE

Battery Power: Indicates how much life is left on the battery.

Power: Slide to turn on remote power.

#3

Q#: Displays the current question number.

Light: Press to turn on backlight (can be disabled by presenter).

Send: Press to submit answer.

#42

ID#: Displays the remote number.

C

Clear: Press to delete answer.

Menu: Press to view menu options. Here you can enter a different session ID or search again for the host.

Thumb pad: Press to navigate between letters in word input questions.

Question: Press to signal help to teacher during a presentation.

Q5 RF

Remote Setup

Before you can use your remotes you must specify the remote type within the Remote Options window. The following steps show how to set up and test your Q5 remotes:

To set up & test remotes:

• Plug the Receiver into an open USB port.

• Open Qwizdom Interact.

• Click on the *Remotes* button. The Remote Options window will appear.

• Click on the *Change* button.

• Select *Q5 RF Remote with Large Display*.

• Check the *Teacher Remote* box if using a teacher remote.

• Under *Student Remotes,* specify the lowest and highest remote numbers used in the set.

• Check *Classroom Set* if your set of remotes are used only in a single classroom. This uses a fixed number for every remote and does not require students to enter session & student ID's during activities.

• Check *Roaming or Student Owned* if remotes are used in more than 1 classroom with different receivers. This reassigns a new number to remotes during every activity and requires that students ente session & student ID numbers.

• If you selected *Classroom Set*, click *Assign Fixed Numbers* to assign remotes a fixed number to them. A session ID number will appear on-screen. Enter this number on each remote & press *Send*.

• Click on *Test* and turn on all the remotes. The Test Remote window will appear with each remote number listed in a gray box.

• Hit any key on a remote to test it. If the remote is working properly, the box containing the remote number will change the color to blue.

• When you are done, select *Close* to exit the Test Remotes window. You will be taken back to the Remote Options window.

• Click *OK* to exit.